

QUICK SETUP GUIDE

Face Recognition Lobby Phone **K6B LP-S700MF**




www.kocom.com

※Thank you for purchasing our product. Read safety instructions and manual carefully before using the product.
※This manual is based on the date as shown in the right and specifications are subject to change without notice for quality improvement

How to install


- Install the power supply DC 24V in the flush box
- Connect the power supply output to POWER IN terminal of the lobbyphone (DC24V+,GND)
- Connect the MAIN line to the house LINE connection part of the lobby phone



Product Installation Location Guide

Standard height for lobby phone installation

The standard height of the lobby phone is 1,450~1,500 from the bottom based on the bottom of the lobby phone flush box. If the height of the lobby phone is out of the range of 1,250mm to 1,550mm, it is impossible to adjust the desired image only by adjusting the angle of the lens, so be careful of height when installing the lobby phone.



Directly connecting cut-off power cord with power wire


- 1) Do not do such electric work on your own. Installing product in this way requires reliance on electric installation man with electric work license.
- 2) Insulate with insulating tape while cutting off power cord and connecting with power wire so electric wire metal does not expose. Contact between exposed electric wires cause fire or electric shock accident.
- 3) Such electric work requires connection after interception of supplied power.

Product specification


Product name	K6B LP-S700MF (Lobbyphone)
Input power type	DC 24V, In stand-by : 7.5W / In operation : 12W
Display	7-inch IPS LCD
DATA communication	RS485
Talking method	Hands-free (1WAY)
Call and image retention time	Waiting time of about 30 seconds after call, About 3 minutes during house talk
Exterior materials	Aluminum (AL), ABS, tempered glass
Size	240(W) x 300(H) x 56(D) mm
Operation guaranteed temperature	-10℃ ~ 50℃
Mount type	Flush Mount
LED lighting function	1LED temporary lighting of 15 button part
Camera pixel	520,000 pixels
RF card interlocking	13.56Mhz
Interlocking device	Guardphone : KAM-305(8 Line), K6B GP-70K(K6B Line) HUB : KHU-305, KHU-320 House monitor : K6B monitor, Compatible monitors with KHU-305
Input/Output specifications	· POWER IN, OUT Connection : 254mm pitch 2P x 2- · SENSOR Connection : 2mm pitch 5P x 1 · DOOR Connection : 2.54mm pitch 3P x 1 · DVR image connection : 2mm pitch 2P x 1
Wiring specifications and Maximum wiring distance	· DC24V Adapter ~ Lobbyphone --- 5m (Separately TIV x 2C) · Lobbyphone ~ GuardPhone Communication, call : 300m (CAT5 UTP) · Lobbyphone ~ Videophone Communication, call : 300m (CAT5 UTP) · Lobbyphone ~ Videophone Video : 20m (CAT5 UTP) ※Lobbyphone ~ Videophone Video : 100m (Separately Coaxial Cable) · Lobbyphone ~ DVR Video : 20m (CAT5 UTP) ※Lobbyphone ~ DVR Video : 100m (Separately Coaxial Cable) · Lobbyphone ~ Sensor Interlocking Device : 10m (CAT5 UTP) · Lobbyphone ~ DOOR Interlocking Device : 5m (CAT5 UTP)

Connection Diagram



Sensor connection diagram




Automatic door connection diagram




Product terminal



· Connection diagram of K6B multi-unit house system



· Connection diagram of K6B main system



· User Face Registration

01. Entering setting

· Press "Household No." + "*" in Idle Screen.



02. Using household password

· Press a 4-digit household password to move to the screen for Face Registration.





03. Use RF Card

· Touch the RF Card registered in the relevant household to move to the screen for Face Registration.




04. Face Registration

· Displaying the number of faces registered in the household as "[0]".
· Position the fact at the center of the screen and press "Security" to save.



05. Face Deletion

· Press "Page" button and the pop-up window for guidance for deletion appears.
· Press "Security" button to delete all the information registered in the household No.



View product details manual
Please scan the QR code with your smartphone.

